



**Tough, yet small
enough to fit in
your pocket !**

SPECIFICATIONS

3½ digit LCD display with annunciators

Display hold DH button

Display update 25 times per second

AC A: 10mA to 200A,
autoranging (2 ranges)
(40Hz to 500Hz)

Max conductor: 27mm Ø

Operating temperature: 0° to 40°C at <80% RH

Auto Power off after 10 mins

Low battery warning: “BAT” symbol

Overrange indication: “OL” symbol

Dimensions: 150 x 52 x 24mm

Weight: 110g

Overvoltage: Category III, 300V

Includes: battery, carry case and user manual

The Martindale CM51 is a low cost 200A mini clamp meter with autoranging, display hold and auto power down.

The two ranges mean that when measuring 40A and lower currents the resolution increases from 100mA to 10mA. Autoranging ensures that the most suitable range is always automatically selected.

This current clamp is small enough to fit into your shirt pocket yet still makes accurate measurements.

The small jaws make it easy to use with the 200A AC range covering the majority of applications.

Martindale Electric Company Ltd.

Metrohm House, Penfold Trading Estate, Imperial Way, Watford, WD24 4YY. Tel: 01923 441717 Fax: 01923 446900

Visit our website: www.martindale-electric.co.uk email: sales@martindale-electric.co.uk